

An algorithm for three-dimensional indoor positioning based on Bayesian inference, Fingerprinting method and Wi-Fi technology

Hitalo Nascimento, Francisco R.P. Cavalcanti, Emanuel B. Rodrigues, Antônio R. Paiva

GTEL - Wireless Telecom Research Group, Department of Teleinformatics Engineering, Federal University of Ceara, Fortaleza, Brazil.

Abstract—Wireless indoor positioning systems have been shown to be very useful in many applications and have been the subject of a considerable amount of research, mainly concerning the two-dimensional (2D) case. However, in many practical situations it is necessary to determine the three-dimensional (3D) coordinates of an object or user. In this paper, a hybrid algorithm for implementation in a 3D indoor positioning system is proposed. This algorithm is implemented by using a fingerprinting technique based on both the k-means and naive Bayes methods, and uses the received signal strength (RSS) as an input parameter. In addition, a comparison of the main algorithms discussed in previous research papers and the proposed algorithm is presented. Indoor positioning experiments were conducted in a typical building with two floors (180m²) and four access points (APs).

The proposed algorithm exhibited a better performance than that of other algorithms, with a mean error around 1.80m.

Keywords—3D Indoor positioning, Fingerprint, Naive Bayes, k-means, Cost 231 multi-wal.

I. INTRODUCTION

Technological development has made the location of both people and objects in outdoor environments possible by means of tools such as the Global Positioning System (GPS). However, these tools are not efficient for handling indoor locations because the variability of these environments is high as compared that of outdoor environments. This is because the variability depends not only on the antenna's characteristics, but also on the type of construction and internal structures, such as the walls, floors, and partitions walls.

Because of the numerous applications of indoor positioning systems (IPS), including utilization in emergency systems, localization of mobile robots, and navigation assistance in malls, schools, university campuses, airports, and hospitals, several studies have

been conducted on location estimation in this type of environment.

A survey of the main implementation techniques shows that they can be classified into three typical location estimation schemes: triangulation, scene analysis (fingerprinting technique), and proximity. These schemes are discussed in [1] and [2], whereas in [3] and [4] the application of artificial neural networks (ANNs) to the problem was proposed. The k-nearest neighbours (k-NN) algorithm and the Bayes method were addressed in [5], [6], [7], [8] and [9].

In this paper, we propose a three-dimensional (3D) solution to this problem through a hybrid algorithm. This algorithm is implemented by using a fingerprint technique based on both the k-means and naive Bayes methods, and uses the received signal strength (RSS) as an input parameter. Furthermore, we compare the proposed method with the ANN multilayer perceptron (MLP) and radial basis function (RBF) algorithms, as well as with the k-NN and Bayes (histogram and kernel) methods and the method of triangulation (lateration), which is one of the most commonly used methods in the context of outdoor locations.

The experiments were conducted in two distinct scenarios, both in a typical build with a total area of 180m² (first floor 131m² and second floor 49m²) and four APs. In the first scenario, actual measurements were performed and the RSS values obtained in pre-defined regions. In the second scenario, the signal behavior was simulated from the Cost 231 multi-wall (MWM) model. The rest of this paper is structured as follows: Section II presents an overview of the main techniques and technologies related to indoor positioning, proposed algorithms are discussed in section III, section IV presents the main discussions and computational results and finally, section V summarizes the results and presents suggestions for future work.

II. INDOOR POSITIONING SYSTEMS

2.1 METHODS FOR INDOOR POSITIONING SYSTEM

In literature, the indoor positioning system can be classified into three main categories: triangulation (method based on geometric properties), fingerprint (signal data collection or pattern recognition technique) and proximity. A comparison of these methods is presented in [1].

2.1.1 TRIANGULATION

The Triangulation method uses geometric properties of triangles to estimate the target location [1] and [2]. This method is classified into two categories:

- Lateralation: estimates user location by calculating the distance between the mobile unit and a set of APs with known coordinates. For a 3D positioning, it is necessary at least four APs. Centered on each of the APs, a sphere with radius r , being the location of the user defined by the intersection of such spheres. Figure 1 shows this concept.




Fig. 1: Indoor Positioning System Based on Lateralation

- Angulation: The location of the target can be estimated by the intersection of several pairs of lines with respect to the direction of the angles, each formed by the circular radius from a set of APs. Figure 2 shows this concept.




Fig. 2: Indoor Positioning System Based on Angulation

The most common methods used to estimate distance in the triangulation method are [1]:

- Time of Arrival (TOA): The distance between the mobile unit and the unit of measurement is directly proportional to the propagation time. For 3D positioning, TOA measurements must be performed in relation to the signals of at least four APs.
- Time Difference of Arrival (TDOA): It consists of a variation of the TOA, however, the estimation of the mobile unit is obtained from multiple measurements in order to obtain the difference between the arrival times of the signal to the receiver.
- Received Signal Strength (RSS): This technique is based on attenuation of the signal between multiple transmitters and the receiver. The estimation of the difference between transmitted and received RSS is determined through empirical and theoretical propagation models. Some of these models are discussed in [10].

A comparison of the methods in question, including parameters such as cost and accuracy, is presented in [11].

2.1.2 FINGERPRINT

Fingerprint is a technique based on pattern recognition and involves the division of the location system into two phases, offline and online phases. In the offline phase, the vectors of received signal strength are collected the of all the detected Wi-Fi signals from different access points at many known locations (reference points) [8]. The online phase consists of reading an RSS value, and by using a classification algorithm, this RSS value is compared with the values stored in the database during the offline phase, thus obtaining the location. The Figure 3 summarizes this procedure.




Fig. 3: Indoor Positioning System Based on Fingerprint

2.1.3 PROXIMITY

Among the three methods for indoor location, the proximity method is considered the simplest. Location systems based on this method do not provide a coordinate as a user location estimate. In this case, the indoor

position is given sectorally, that is, the system returns the room in which the user can be at a given time. Technologies used by this method include radio frequency identification and Bluetooth [1].

2.2 TECHNOLOGIES FOR INDOOR POSITIONING

2.2.1 Radio Frequency Identification - RFID

It consists of a technology that uses radio waves to identify people or objects. Identification can be obtained by reading information stored in a tag attached to an object. Some works that use this technology include [13], [14] and [15].

2.2.2 Wi-Fi

It is a technology that uses radiofrequency to transmit data from devices based on one of the 802.11 standards developed by the IEEE. These devices include for example: Notebooks, cell phones, cameras and TV's, which makes this technology more suitable for implementing an IPS [16].

2.2.3 Bluetooth

It is often classified as a wireless personal area networks (PANs) technology, with transmission power and range much smaller than a Wi-Fi network, occupying a limited space around the user (usually 10 meters). It is used to connect wireless devices within a short distance, such as: Cellular phones, TV's, notebooks and stereos. For more detailed discussions on the application of this technology to the problem in question, see [17], [18], [19], [20] and [21].

III. PROPOSED SOLUTION AND GENERAL DESCRIPTION OF THE SYSTEM

3.1 METHODS FOR INDOOR POSITIONING SYSTEM

The proposed algorithm is based on Bayesian inference and use the fingerprint technique as the basic structure for estimating the location. The algorithm consists of a combination of the k-means and the naive Bayes, a simplified version of the Bayes theorem discussed in the subsection 3.3. The Bayes theorem is given by [22]:

$$P(x_i|y) = \frac{P(y|x_i)P(x_i)}{\sum_{k=1}^N P(y|x_k)P(x_k)} \quad (1)$$

The central idea of the proposed method is to determine the most probable position of the target based on the RSS vector measured in relation to all n APs. This procedure is performed through the following rule:

Let $\mathcal{S}_1, \mathcal{S}_2, \dots, \mathcal{S}_N$ be a collection of subsets, called sectors or rooms, where each is a candidate for target location and consists of n RP's where $\cap_{i=1}^N \mathcal{S}_i = \emptyset$ and $\cup_{i=1}^N \mathcal{S}_i = \mathcal{A}$, represents the indoor space for the set of sectors and $\mathbf{s} = \{RSS_1, RSS_2, \dots, RSS_N\}$ the RSS vector observed during the online phase. Select \mathcal{S}_i , if

$P(\mathcal{S}_i|\mathbf{s}) > P(\mathcal{S}_j|\mathbf{s})$, for $i, j = 1, 2, \dots, N$ and $i \neq j$. This results in the following model:

$$P(\mathcal{S}_i|\mathbf{s}) = \frac{P(\mathbf{s}|\mathcal{S}_i)P(\mathcal{S}_i)}{\sum_{t=1}^N P(\mathbf{s}|\mathcal{S}_t)P(\mathcal{S}_t)} \quad (2)$$

When the sector that represents maximum probability is selected, the 3D location of the target is defined from the centroid of the RP's belonging to the sector in question.

3.2 ESTIMATION OF THE LIKELIHOOD FUNCTION

Let $\mathbf{x} = \{x_1, x_2, \dots, x_N\}$ an RSS sample obtained from an unknown probability distribution with density $f_X(x)$, in the off-line phase of the location system, our objective is to estimate the density in question. There are several methods for this estimate. The most common are presented below:

- Histogram: this method subdivides the space of $f_X(x)$ with support $[0,1]$ in n bins of (Sectors of \mathcal{A}) equal sizes, given by:

$$B_1 = [0, \frac{1}{n}], B_2 = [\frac{1}{n}, \frac{2}{n}], \dots, B_N = [\frac{n-1}{n}, 1] \quad (3)$$

To estimate $P(\mathbf{s}|\mathcal{S}_i)$, we obtain the frequency distribution of the signals in the environment. The goal is to check the frequency of each RSS interval for all locations.

- Density estimation Kernel (EDK): In probability and statistics, EDK, is a non-parametric method for estimating a probability density function $f_X(x)$ given by: [9].

$$f_X(x) = \frac{1}{nh} \sum_{i=1}^N K\left(\frac{x - X_i}{h}\right) \quad (4)$$

Where n is the sample size. h is a non-negative data smoothing parameter called bandwidth. Similar to the histogram method, the kernel estimation establishes a function for representing the probability distribution, with the difference that the data is not to be allocated in discrete regions (bins), instead a continuous function is defined. $K(\bullet)$ is the kernel function in which:

$$\int_{\mathbb{R}} K_X(x) dx = 1 \quad (5)$$

A widely used function in this case is the Gaussian kernel [9]. Thus, the estimate for the term $P(\mathbf{s}|\mathcal{S}_i)$, can be modeled through a normal distribution is given by:

$$f_X(x) = \frac{1}{N} \sum_{i=1}^N \frac{1}{h\sqrt{2\pi}} \exp\left[-\frac{1}{2}\left(\frac{RSS - RSS_i}{h}\right)^2\right] \quad (6)$$

3.3 PROPOSED SOLUTION (KMEANS-BAYES)

The implementation of an IPS through this algorithm divides the off-line phase into two steps. The first step starts with reading the RSS vectors in n RP's with predetermined 3D positions that make up the vector r . For each RP, measurements are taken for all APs. In addition, these measurements are performed at different heights and with the mobile device directed to the north, south, east and west. This results in the following matrix:

$$A = \begin{pmatrix} RP_1(z_1) & RP_2(z_1) & \cdots & RP_N(z_1) \\ RP_1(z_2) & RP_2(z_2) & \cdots & RP_N(z_2) \\ \vdots & \vdots & \ddots & \vdots \\ RP_1(z_N) & RP_2(z_N) & \cdots & RP_N(z_N) \end{pmatrix} \quad (7)$$

This procedure aims to make the database robust, thus maximizing the accuracy of the algorithm. When all measurements are completed, in the second step, the k -means algorithm partitions the indoor space into P clusters that represent the sectors in which the RP's will be allocated. For each of the clusters a set of centroids with Cartesian coordinates randomly chosen in the first iteration is defined. From the second iteration, the centroids are obtained based on the mean coordinate of the RP's. In addition, a value for P is defined. Then, the distance between each RP and the centroids is calculated by assigning each RP to the cluster that has the nearest centroid. This procedure is repeated until there is no RP change between the clusters.

This procedure is performed by minimizing an objective function, called the squared error function, which is defined as

$$J = \sum_{j=1}^P \sum_{i=1}^N \|r_i - c_j\|^2 \quad (8)$$

Where $\|r_i - c_j\|$ is a 3D measure of the distance between each reference points and the centroid. In general, Euclidean distance is applied in (8). This, together with other measures of similarity, including Mahalanobis, Minkowski, and cosine distances, are discussed in [23].

When the clustering process is completed, there have the following configuration:

- Each RP has a definite 3D coordinate $P = (x, y, z)$ and an RSS vector related to this coordinate.
- are assigned probabilities for each of the clusters, according to the knowledge of the frequency of users in each of these clusters or evenly, that is, considering that $P(\mathfrak{P}_i), i = 1, \dots, N$ are equiprobable.

After this procedure, the offline phase is complete.

In the online phase the vector $s = \{RSS_1, RSS_2, \dots, RSS_N\}$ is read and the target position is estimated based on equation (2), resulting in:

$$P(\mathfrak{P}_i | s) = \frac{P(s | \mathfrak{P}_i) P(\mathfrak{P}_i)}{P(s)} = \frac{P(RSS_1, RSS_2, \dots, RSS_N | \mathfrak{P}_i) P(\mathfrak{P}_i)}{P(s)} \quad (9)$$

Using the general multiplication rule [24] in (9), results in:

$$P(RSS_1, RSS_2, \dots, RSS_N | \mathfrak{P}_i) = P(RSS_1 | RSS_2, \dots, RSS_N, \mathfrak{P}_i) \times P(RSS_2 | RSS_3, \dots, RSS_N, \mathfrak{P}_i) \times \dots \times P(RSS_{N-1} | RSS_N, L_i) \cdot P(RSS_N | \mathfrak{P}_i) \quad (10)$$

In order to reduce the computational cost of system incurred by equation (9) when it is necessary to acquire a large volume of data, we will consider that the probability of each attribute of vector s are independent of each other given the locations. This means that $P(RSS_1, RSS_2, \dots, RSS_N | \mathfrak{P}_i)$ can be simplified:

$$\prod_{i=1}^N P(s | \mathfrak{P}_i) \quad (11)$$

Thus, the target position given s is simplified to:

$$\begin{aligned} P(\mathfrak{P}_i | s) &\propto P(\mathfrak{P}_i, RSS_1, \dots, RSS_N) \\ &\propto \mathfrak{P}_i \times P(RSS_1, \dots, RSS_N | \mathfrak{P}_i) \\ &\propto P(\mathfrak{P}_i) \times P(RSS_1 | \mathfrak{P}_i) \times \dots \times P(RSS_N | \mathfrak{P}_i) \\ &\propto P(\mathfrak{P}_i) \prod_{i=1}^N P(s | \mathfrak{P}_i) \end{aligned} \quad (12)$$

Algorithm 1 Hybrid algorithm: k -means and naive Bayes for three-dimensional indoor positioning in wireless local area networks

Input: $r = \{RP_1, RP_2, \dots, RP_N\} \in \mathbb{R}^n$ that represents the vector of reference points.
Number of clusters P representing the number of sectors.
A signal vector $s = \{RSS_1, RSS_2, \dots, RSS_N\}$.

Output: A 3D position from the centroid coordinate of the RP's.

- 1: Define a set of centroids c_1, c_2, \dots, c_P . Define a set of centroids with random coordinates for each cluster.
- 2: **repeat**
- 3: Calculate distances between the RP's and the centroids using equation (8) and assign each point to the cluster with the closest centroid.
- 4: Recompute the centroid of each cluster based on the coordinates of the RP's.
- 5: **until** converged (there is no movement of data between the clusters)
- 6: **for** $i=1$ to N **do**
- 7: Compute $P(\mathfrak{P}_i | s)$ based on equation (10).
- 8: **end for**
- 9: Allocate the target to the cluster that results in the maximum probability.
- 10: Get the RP's centroid.
- 11: **Return** 3D positioning based on the coordinates obtained in step 10.

Equation (12) is a simplified version of the Bayes theorem, known as the Naive Bayes. More details on this classifier can be obtained in [22]. After the cluster that result in maximum probability has been identified, the target position is estimated from the centroid coordinate of the RP's. Algorithm 1 and figure 4 summarize the proposed method.




Fig. 4: IPS K Means-Bayes based on fingerprint method

IV. EXPERIMENTAL RESULTS AND DISCUSSION

4.1 INTRODUCTION

The experiments were conducted in two distinct scenarios, both in a typical build with a total area of 180m² (first floor 131m² and second floor 49m²) and four APs. In the first scenario, actual measurements were performed and the RSS values obtained in pre-defined

regions. Figure 5 shows the floor plan with for the two floors used in experiments. In order to make the developed IPS more realistic, all experiments were performed in the environment with people performing their normal activities.



Fig. 5: Floor Plan used in experiments and simulations

In the second scenario, the same build was considered, taking into account all the characteristics of this environment (for example, the quantity, position and transmit power of the Aps), with the difference that in the scenario in question no real measurements were. Instead, the Cost 231 multi-wall model (MWM) was used to simulate the behavior of the signal in this residence. This model considers the signal attenuation as the loss in free space added to the loss resulting from the numbers of walls and floors penetrated between the transmitter (T_x) and receiver (R_x). The model in question is given by [10].

$$L = L_{LF} + L_c + \sum_{i=1}^I k_{wi} L_{wi} + k_f^{\frac{L_f+2}{k_f+1}-b} L_f \quad (13)$$

where

- L_{FS} = free space loss between transmitter and receiver;
- L_c = constant loss;
- k_{wi} = number of penetrated walls of type;
- k_f = number of penetrated floors,
- L_{wi} = loss of wall type;
- L_f = loss between adjacent floors,
- b = empirical parameter;
- I = number of wall types.

The total loss related to the floors is a non-linear function of the number of penetrated floors [10]. This feature is taken into account by the introduction of an empirical factor b . For practical reasons, the number of distinct walls should be kept low because the difference between

the various wall types in relation to the attenuation is small and its meaning in the model is not clear [10]. The types of walls in question are displayed in the table 1 [10], while the typical values of L_{w1} , L_{w2} , L_f , and b are shown in the table 2 [10].

Table.1: Types of walls used in the Cost 231 MWM

Wall type	Description
Light wall (L_{w1})	A wall that is not bearing load: e.g. plasterboard, particle board or thin (<10 cm), light concrete wall.
Heavy wall (L_{w2})	A load-bearing wall or other thick (>10 cm) wall, made of e.g. concrete or brick.

Table.2: Values for L_{w1} , L_{w2} , L_f e b in dB

Environment	Multi-wall model (MWM)			
	L_{w1} [dB]	L_{w2} [dB]	L_f [dB]	b
Dense one floor two floors multi floor	3.4	6.9	18.3	0.46
Open	3.4	6.9	18.3	0.46 ⁹⁾
Large	3.4	6.9	18.3	0.46 ⁹⁾
Corridor	3.4	6.9	18.3	0.46 ⁹⁾

4.2 PARAMETERS OF ALGORITHMS

As algorithms for comparison, the main solutions addressed in the literature were chosen. The following parameters were used:

- Triangulation: Let $D = (x, y, z)$ be the coordinate representing the location of the target, given by

the intersection of four spheres centered on four APs with known coordinates given by (x_1, y_1, z_1) , (x_2, y_2, z_2) , (x_3, y_3, z_3) and (x_4, y_4, z_4) whose distances to the target are given by d_i^2 with $i = 1, 2, \dots, 4$, estimated by the attenuation of RSS, we obtain the location of the target from the following relation:

$$\begin{cases} (x - x_1)^2 + (y - y_1)^2 + (z - z_1)^2 = d_1^2 \\ (x - x_2)^2 + (y - y_2)^2 + (z - z_2)^2 = d_2^2 \\ (x - x_3)^2 + (y - y_3)^2 + (z - z_3)^2 = d_3^2 \\ (x - x_4)^2 + (y - y_4)^2 + (z - z_4)^2 = d_4^2 \end{cases} \quad (14)$$

- KNN: For this algorithm, we considered the value of $k = 2$ and 3 . Where k represents the number of nearest neighbors. In addition, Euclidean distance was used as a measure of similarity;

- Artificial neural networks (MLP and RBF):

Table.3: Parameters Adopted for the Neural Networks

Parameters	Value
Number of neurons in the input layer	20
Number of neurons in the output layer	3
Number of neurons in the hidden layer	50, 100, 150 200, 250 e 300
Number of hidden layers	2 MLP e 1 RBF
Activation Function	Sigmoide
Training algorithm	Backpropagation
Learning rate	0,04
Number of iteration	5000

Probabilistic Model (Pure version of Bayes theorem): In

this case, the IPS was developed through equation (2). using the histogram and kernel based versions. The kernel method was modeled by a distribution by a normal distribution, according to equation (6).

4.3 RESULTS OF SCENARIO I

For this scenario, it was considered 150 RP's distributed in the two floors. For each PR, 300 RSS values were collected, according to the following rule: Notebook with heights of 0.2m; 1.0m and 1.80m. In each height, 25 measurements were performed with a notebook with the Notebook facing toward the north, east, south, and west directions. The Vistumbler software [25] was used to acquire RSS.

After reading the RSS in all RPs, an experiment was conducted to verify the variation of the signal in the environment. At a fixed point (15.2.0.7 and 5.72m), for a period of 300s the signal strength Signal strength was observed with respect to the four APs. The results are shown in the figure 6. Note that even from a fixed position, the fluctuations in the signal level reaches 10 dB, which is the expected variability for indoor environments.

With respect to the performance of the algorithms, the method of lateration when compared with others was not efficient. This is an expected result, since methods based on traditional outdoor location are not suitable for indoor environments, which have a much greater variability [11]. The system implemented with this method showed a mean error e_m of 2.23m from the actual location with precision of 68 % and 80.1% relative to absolute maximum error e_a of 1.5 and 3.5m respectively.




Fig. 6: Variations of RSS values from four APs in a fixed point

Table.4: Statistics of positioning estimates

ALGORITHM	ϵ_a (%) $\leq 1.5m$	ϵ_a (%) $\leq 3.5m$	ϵ_a (%) $\leq 5.5m$	ϵ_a (%) $\leq 7.5m$
Lateralation	68,2	80,1	87,8	95,1
kNN = 2	75,8	88	94,8	98,9
kNN = 3	76,1	88,7	95,3	99,1
RNA - MLP	76,2	89	95,8	99,3
RNA - RBF	76,65	89,6	96,5	99,4
HISTOGRAM	76,9	90,8	98	100
KERNEL	77,2	91,2	98,6	100
PROPOSED METHOD	77,9	93,1	98,9	100

Table.5: Statistics of positioning estimates (average, coefficient of variation, Q1, Q2, and Q3 quartiles in meters)

ALGORITHM	ϵ_m	C_v	Q1	Q2	Q3
Lateralation	2.235	59.70%	1.36	1.73	2.57
kNN = 2	1.919	45.22%	1.33	1.66	1.93
kNN = 3	1.916	44.16%	1.33	1.66	1.91
RNA - MLP	1.905	43.15%	1.33	1.66	1.90
RNA - RBF	1.883	41.89%	1.33	1.65	1.88
HISTOGRAM	1.843	37.97%	1.32	1.65	1.86
KERNEL	1.832	36.80%	1.32	1.65	1.84
PROPOSED METHOD	1.803	35.06%	1.32	1.64	1.81




Fig. 7: Error in meters - cumulative

4.4 RESULTS OF SCENARIO II

In this scenario, equation (13) was used to simulate the signal behavior in the environment. In addition to the

estimation of the RSS attenuation applied to the lateration method, this simulation includes the estimation of the vectors RSS in each PR. It was observed that in the scenario in question, the lateration method presented performance superior to that implemented in scenario I. This better performance can be explained by the smaller variation in the signal compared to scenario I, because although the propagation model used in this work is considered more complete with respect to the others, in order to include the losses from the various obstacles, can not accurately represent the signal fluctuations in the various types of indoors environments. Even with better performance in this scenario, the lateration method was less accurate than the others, presenting ϵ_m of 2.0m, against the most similar algorithm in terms of performance (kNN with $k = 2$) that it obtained ϵ_m of 1.92m. In relation to the other algorithms, there were no significant differences in performance (Algorithms based on the fingerprint method, are less influenced by the variation of RSS in the environment). The proposed method presented ϵ_m equal to 1.786m. The results are summarized in the tables 6, 7 and in the figure 8.

Table.6: Statistics of positioning estimates (average, coefficient of variation, Q1, Q2, and Q3 quartiles in meters)

ALGORITHM	ϵ_a (%) $\leq 1.5m$	ϵ_a (%) $\leq 3.5m$	ϵ_a (%) $\leq 5.5m$	ϵ_a (%) $\leq 7.5m$
Lateralation	72,9	87,4	93,70	97,8
kNN = 2	76	88,1	95	99
kNN = 3	76,05	88,5	94,98	99
RNA - MLP	76,5	88,7	95,55	99,7
RNA - RBF	76,66	89,5	96,3	99,8
HISTOGRAM	77	91	97,9	100
KERNEL	77,1	91,3	98,5	100
PROPOSED METHOD	79,1	93	98,8	100

Table.7: Statistics of positioning estimates (average, coefficient of variation, Q1, Q2, and Q3 quartiles in meters)

ALGORITHM	ϵ_m	C_v	Q1	Q2	Q3
Lateralation	2.002	51.60%	1.34	1.69	2.00
kNN = 2	1.924	44.89%	1.33	1.66	1.92
kNN = 3	1.908	44.92%	1.33	1.66	1.91
RNA - MLP	1.897	43.59%	1.33	1.66	1.92
RNA - RBF	1.880	42.38%	1.33	1.65	1.88
HISTOGRAM	1.841	38.13%	1.32	1.65	1.85
KERNEL	1.791	35.07%	1.31	1.63	2.00
PROPOSED METHOD	1.786	34.54%	1.31	1.63	2.00




Fig..8: Error in meters – cumulative

V. CONCLUSION

In this paper, we propose a three-dimensional (3D) solution to this problem through a hybrid algorithm. In addition, a comparison was made with the main algorithms discussed in previous research papers, including with the lateralation method, one of the most used in the outdoor context. With the exception of this method, all algorithms used a fingerprint recognition technique.

A lower variation in signal levels in Scenario II had a direct influence on the performance of the lateralation method. In this scenario, the lateralation obtained better performance than in scenario I (around 23cm in relation to ϵ_m). Even with better performance in this scenario, the lateralation method was less accurate than the others, which also demonstrated better performance compared to scenario I, but not significantly. As discussed, indoors environments have high variability. IPS developed only

from simulations based on propagation models may not capture all the information regarding the signal variations in this type of environment and therefore, overestimate the results, as in the case of the lateralation method implemented in this work.

The proposed algorithm exhibited a better performance than that of other algorithms, resulting $\epsilon_m = 1.80$ and 1789 for scenarios I and II respectively. Because the proposed algorithm is based on Bayesian inference, there is good integration with the fingerprint technique, this because it relates the current and past information efficiently, which results in good results in relation to the classification. However, one of the limitations of the techniques in question is related to the quality of the information, that is, a robust database is necessary for an IPS based in this algorithm to present good results.

As future work, we intend to develop the following solutions in order to maximize the precision of the location estimation:

- IPS based on angulation;
- Hybrid IPS based on triangulation and fingerprint;
- IPS based on multiple discriminant analysis.

REFERENCES

- [1] Hui, L., Houshang, D., Banerjee, P., Jing, L.: 'Survey of wireless indoor positioning techniques and systems', IEEE Transactions on System, Man, and Cybernetics-Part C: Applications and Reviews, Vol. 37, No. 6, 45-61, Nov. 2007. doi=10.1109/TSMCC.2007.905750, ISSN=1094-6977.
- [2] 2. R. Harle.: 'A Survey of Indoor Inertial Positioning Systems for Pedestrians', IEEE Communications Surveys Tutorials, Third Quarter 2013, vol. 15, No. 3, 1281-1293, doi: 10.1109/SURV.2012.121912.00075.
- [3] Nerguizian, C., Despins, C., Affes S.: 'Geolocation in mines with an impulse response fingerprinting technique and neural networks', IEEE Transactions on Wireless Communications, Mar. 2006, VOL. 5, No 3, pp. 603-611, doi: 10.1109/TWC.2006.1611090
- [4] Kung, H.Y., Chaisit, S., Phuong, N.T.M.: 'Optimization of an RFID location identification scheme based on the neural network', International Journal of Communication Systems, Mar. 2015, VOL. 28, No. 4, pp. 625-644
- [5] Dong, L., Baoxian, Z., Cheng, L.: 'A feature-scaling-based k-nearest neighbor algorithm for indoor positioning systems', IEEE Internet of Things Journal, Aug. 2016, VOL. 3, No. 4, pp. 590 - 597
- [6] Niu, J., Wang, B., Shu, L., Duong, T.Q., Chen, Y.: 'ZIL: An Energy-Efficient Indoor Localization System Using ZigBee Radio to Detect WiFi Fingerprints', IEEE Journal on Selected Areas in Communication, July 2015, VOL. 33, No7, pp. 1431-1442, doi: 10.1109/JSAC.2015.2430171

- [7] Madigan, D., Einahrawy, E., Martin, R.P., Ju, W. H., Krishnan, P., Krishnakumar, A.S.: 'Bayesian indoor positioning systems', *Proc. IEEE INFOCOM*, 2005, VOL. 2, No 5, pp. 1217-1227, doi: 10.1049/ietrsn.2014.0108
- [8] Morales, J.A., Akopian, D., Tirri, H., Agaian, S.: 'Faulty measurements impact on wireless local area network positioning performance', *ET Radar, Sonar Navigation*, 2015, VOL. 09, No 5, pp. 501-508, doi: 10.1049/ietrsn.2014.0108
- [9] Roos, T., Myllymaki, P., Tirri, H., Misikangas, P., Siev'anen J.: 'A probabilistic approach to WLAN user location estimation', *International Journal of Wireless Information Networks*, 2002, VOL 09pp. 45-61
- [10] COST 231 Multi-Wall Digital Mobile Radio Towards Future Generations Systems, Final Report European Commission, pp. 176-179. ISBN 92-828-5416-7, 1999
- [11] Shweta, S., et al.: 'Localization Techniques in Wireless Sensor Networks', *International Journal of Computer Science and Information Technologies (IJCSIT)*, 2015, VOL. 6, No 1, pp. 844-850, doi: 10.1109/COMST.2015.2464084
- [12] He, S., Chan, S.H.G.: 'Wi-Fi fingerprint-based indoor positioning: Recent advances and comparisons', *Technical Report 4, USAF School of Aviation Medicine, Randolph Field*, First quarter 2016, VOL. 18, No 1, pp. 466-490, doi: 10.1109/COMST.2015.2464084
- [13] C. Wang, Z. Shi, F. Wu and J. Zhang, "An RFID indoor positioning system by using Particle Swarm Optimization-based Artificial Neural Network," 2016 International Conference on Audio, Language and Image Processing (ICALIP), Shanghai, 2016, pp. 738-742. doi: 10.1109/ICALIP.2016.7846624
- [14] F. Seco, A. R. Jimenez and X. Zheng, "RFID-based centralized cooperative localization in indoor environments," 2016 International Conference on Indoor Positioning and Indoor Navigation (IPIN), Alcalá de Henares, 2016, pp. 1-7. doi: 10.1109/IPIN.2016.7743600
- [15] A. A. W. Ab Razak and F. Samsuri, "Active RFID-based Indoor Positioning System (IPS) for industrial environment," 2015 IEEE International RF and Microwave Conference (RFM), Kuching, 2015, pp. 89-91. doi: 10.1109/RFM.2015.7587719
- [16] Krishnamurthy, P., "Technologies for Positioning in Indoor Areas. In: Indoor Wayfinding and Navigation" RC Press. 2015, pp. 35-51. Print ISBN:978 - 1 - 4822 - 3084 - 0. <https://doi.org/10.1201/b18220-4>
- [17] J. s. Jeon, Y. Kong, Y. Nam and K. Yim, "An Indoor Positioning System Using Bluetooth RSSI with an Accelerometer and a Barometer on a Smartphone," 2015 10th International Conference on Broadband and Wireless Computing, Communication and Applications (BWCCA), Krakow, 2015, pp. 528-531. doi: 10.1109/BWCCA.2015.142
- [18] M. E. Rida, F. Liu, Y. Jia, A. A. A. Algawhari and A. Askourih, "Indoor Location Position Based on Bluetooth Signal Strength," 2015 2nd International Conference on Information Science and Control Engineering, Shanghai, 2015, pp. 769-773. doi: 10.1109/ICISCE.2015.177
- [19] R. Faragher and R. Harle, "Location Fingerprinting With Bluetooth Low Energy Beacons," in *IEEE Journal on Selected Areas in Communications*, vol. 33, no. 11, pp. 2418-2428, Nov. 2015. doi: 10.1109/JSAC.2015.2430281
- [20] Sheng Zhou and J. K. Pollard, "Position measurement using Bluetooth," in *IEEE Transactions on Consumer Electronics*, vol. 52, no. 2, pp. 555-558, May 2006. doi: 10.1109/TCE.2006.1649679
- [21] D. Li and J. Wang, "Research of Indoor Local Positioning Based on Bluetooth Technology," 2009 5th International Conference on Wireless Communications, Networking and Mobile Computing, Beijing, 2009, pp. 1-4. doi: 10.1109/WICOM.2009.5302300
- [22] Pattern Classification (2nd Ed) (Richard O. Duda, Peter E. Hart, David G. Stork), Wiley, 2001.
- [23] Hauskrecht, M., Pelikan, R., Valko, M., Lyons-Weiler, J.: 'Feature selection and dimensionality reduction in genomics and proteomics', Springer, pp. 149-172, Fall 2006, doi: 10.1007/978 - 0 - 387 - 47509 - 7 7
- [24] Schum, D.A.: 'The Evidential Foundations of Probabilistic Reasoning', Northwestern University Press. ISBN: 9780810118218. 1994.
- [25] Software Vistumbler v10.6, <http://www.vistumbler.net/>. Accessed February 2017